

Robin ParFect S1 - DMX chart

Version 1.2

Mode 1- Basic 8 bit, Mode 2- Extended 16bit, Mode 3 - Strobe mode

Mode/Channel			Value	Function	Type of control
1	2	3			
-	-	1	0-31 Shutter closed 32-63 Shutter open 64-95 Strobe effect from slow--> fast 96-127 Shutter open 128-143 Opening pulses in sequences from slow--> fast 144-159 Closing pulses in sequences from fast--> slow 160-191 Shutter open 192-223 Random strobe effect from slow --> fast 224-255 Shutter open	Shutter/Strobe Shutter closed Shutter open Strobe effect from slow--> fast Shutter open Opening pulses in sequences from slow--> fast Closing pulses in sequences from fast--> slow Shutter open Random strobe effect from slow --> fast Shutter open	step step proportional step proportional proportional step proportional step
1	1	2	0-255	Dimmer (8 bit) Dimmer intensity from 0% to 100%	proportional
-	2	3	0-255	Dimmer fine (16 bit) Fine dimming	proportional